

5 W.

1.8" High Definition LGD Colorful Display

- Compatible with MOTOTRBO Digital Radio
- Conform with DMR Tier I&II Standard
- SMS
- Digital Voice Encryption
- Support Private, Group & All Call

DMR



DYNASCAN D-6000
professional radio

DMR Digital Radio Reliable in Quality

Accessories Included:

Antenna



Battery



Charger



Adapter



Belt Clip



DMR Digital Radio

Reliable in Quality

DYNASCAN D-6000

Main Functions

- Frequency 440-470MHz
- High/Low Power Switchable 5W/1W
- High Battery Capacity 2000mAh
- Monitor
- Tail Elimination
- Lone Worker
- SMS
- Repeater
- Talk Around
- Normal/High SQL
- Battery Indicator
- Encryption
- Power Save
- Channel Scanning /Priority Scanning



Technical Specification

GENERAL		TRANSMITTER		RECEIVER	
Frequency Range	440-470MHz	Output Power	5W	Analog Sensitivity	0.35uV/-116dBm(20dB SINAD) 0.22uV/-120dBm(Typical)
RF Output Power	HI Power≤5W Low Power≤1W	Frequency Stability	+/-1.5ppm	Digital Sensitivity	0.3uV/-117.4dBm (BER5%) 0.7uV/-110dBm (BER1%)
Channels	1000 Channels	4FSK Modulation	12.5KHz(data only):7K60FXD 12.5KHz(data+voice):7K60FXE	Adjacent Channel Selectivity	TIA603C:60dB@12.5KHz ETSI:60dB@12.5KHz
Channel Spacing	12.5KHz	Free Time Slot Power	≤ -57dBm	Inter-modulation	TIA603C:65dB ETSI:65dB
CTCSS/DCS	50 CTCSS/ 105 DCS	Modulation Distortion	≤ 3%	Block	≤ -84dB
Antenna Impedence	50 Ω	Digital Audio Encode & Decode	AMBE+2TM	Spurious Response Anti-Interference	TIA603C :70dB ETSI :70dB
Operating Temperature	-30°C+60°C			Rated Output Power	1W
Operating Voltage	DC7.4V			Rated Audio Distortion	≤3%
Battery Type	2000mAh Li-ion				
Dimension(excluding antenna)	133(H) x 61(W) x 40(D)mm				
Weight(Battery,Antenna Included)	About 270g				

Standard Accessories



Antenna



Battery



Charger



Adapter



Belt clip

Este equipo puede ser utilizado en los siguientes países de la UE:

AT	BE	DK	FI	FR	DE	GR	IS	IE	IT	LI
LU	NL	NO	PT	ES	SE	CH	GB	CY	CZ	EE
HU	LV	LT	MT	PL	SK	SI	BG	RO		

Importador exclusivo: www.pihernz.com