

FT-818

HF/VHF/UHF 6W All-Mode Portable Transceiver

Radio Features:

- Increased power output 6W(SSB, CW, FM) 2.0W(AM Carrier) ***NEW!**
- Improved frequency stability ± 0.5 ppm : Built-in TCXO-9 ***NEW!**
- Larger battery capacity : 9.6V/1,900mAh (SBR-32) ***NEW!**
- 5MHz band (WRC-15 frequency) Operation available ***NEW!**
- 208 Memory Channels / 10 Memory Groups
- Operates on 160-10m , HF, 6m, 2m and 70 cm Bands
- Ultra Compact and Portable
- Two Antenna Connectors
- IF Shift, IF Noise Blanker, IPO, ATT
- CW "Semi-Break-in", CW Reverse, CW Pitch Control
- Built-in Electronic Keyer
- Multi-Color Easy to see LCD
- Internal Battery Operation Capability
- ARS Automatic Repeater Shift
- APO Automatic Power Off
- Front Panel Key Lock Mode



FT-818

Supplied Accessories:

Hand Microphone(MH-31A8J)

Battery (SBR-32 9.6V 1900mAh Ni-MH)

Battery Case (FBA-28) (Requires 8 "AA: batteries)

Whip Antenna for 50/144/430 MHz (YHA-63)

DC Cable (E-DC-6)

Shoulder Strap, Ferrite Core, Rubber Foot

Operating Manual

*Battery Charger (PA-48)

*You can select either radio packed with/ without Battery Charger.

Specifications:

Frequency Ranges:	RX	100 kHz - 30 MHz	
		50 MHz - 54 MHz	
		76 MHz - 108 MHz	
		87.5 MHz - 108 MHz	
		430 MHz - 440 MHz	
TX	1.8 MHz - 54 MHz		
	(5.3515 MHz - 5.3665 MHz) WRC-15		
	144 MHz - 146 MHz		
	430 MHz - 440 MHz	(Amateur Bands only)	
Circuit Type:	Double-Conversion Superheterodyne	(SSB/CW/AM/FM)	
	Single-Conversion Superheterodyne	(WFM)	
Modulation Type:	A1A(CW), A3E(AM), J3E(LSB,USB), F3E(FM), F1D(PACKET), F2D(PACKET)		
RF Power Output :	6 W (SSB/CW/FM), 2 W (AM Carrier) @13.8 V		
Memory Channels:	208		
Case Size(W x H x D):	135 x 38 x 165 mm w/o knob and connector		
Weight:	900 g (w/o Battery, Antenna and Microphone)		